



Tech Info Library

HyperCard: Dial Command Problems with Macintosh Portable Modem

Revised: 7/28/92
Security: Everyone

HyperCard: Dial Command Problems with Macintosh Portable Modem

=====

Article Created: 15 April 1991
Article Last Reviewed: 28 July 1992
Article Last Updated:

TOPIC -----

I'm having problems using the Apple Internal 2400 baud modem with the Macintosh portable. The HyperCard Phone stack's dial command just doesn't seem to work with this modem.

DISCUSSION -----

Make sure that the 10-second pause is in the "doDial" handler. Before "put empty", the last line of code in the handler, insert these lines:

```
wait 10 sec  
send return to HyperCard
```

This way the change takes place only once, and it's easier to follow the code at that point. The "return" causes the modem to drop the line, leaving you in voice mode.

The problem with the modem and the Phone stack is that HyperCard opens the serial port for three seconds. It takes the modem around two seconds to go off hook. The dial string contains a comma creating a one-second pause. This leaves hardly any time to send the phone number. The phone number is incompletely transmitted and you get disconnected.

We suggest you use the Serial XCMDs available from APDA for sending data to modems. This command set gives you complete control over the serial port, eliminating the need for the 10-second pause to get the modem to release. (You'll need to recreate the doDial handler to use the serial XCMDs.)

Copyright 1991, Apple Computer, Inc.

Tech Info Library Article Number:7368