



Tech Info Library

Apple IIC: Connecting it to a Smith-Corona TP1 printer

Revised: 2/6/86
Security: Everyone

Apple IIC: Connecting it to a Smith-Corona TP1 printer

=====

On the Smith-Corona TP1 interface circuit board, set the jumpers to match these specifications:

1. 9600 Baud
2. 8 Data Bits
3. No Parity
4. 1 Stop Bit

On the Apple IIC, set the "PIN" configuration using the Apple IIC utilities program. The "PIN" configuration should be set to the same specifications that are listed above.

Cable Pinout

Apple IIC	TP1
2 -----	3
3 -----	7
5 -----	20
4 -----	2

Apple Technical Communications

Tech Info Library Article Number:158