



# Tech Info Library

## DOS Tool Kit: HRCG -- Switching it on and off

Revised: 11/20/84  
Security: Everyone

DOS Tool Kit: HRCG -- Switching it on and off

=====

The High-Res Character Generator can be turned on and off under software control. The following two subroutines will switch back and forth. The software was written assuming the variable "ADRS" is assigned as it is in the subroutine starting at line 2000 of MAXWELL on the Tool Kit diskette.

```
3000 REM          TURN OFF HRCG
3010 PRINT CHR$(4);"PR#0"
3020 PRINT CHR$(4);"IN#0"
3030 HOME
3040 TEXT
3050 RETURN
4000 REM          TURN ON HRCG
4010 CALL ADRS + 3
4020 RETURN
```

Beware: the HRCG overwrites the text screen when outputting to the High-Res screen. It will destroy any information there. You will have to rewrite the text screen after using HRCG.

Apple Tech Notes

Tech Info Library Article Number:548