



Tech Info Library

Racal-Vadic VA212LC modem: Using it with Apple Computers

Revised: 2/10/93
Security: Everyone

Racal-Vadic VA212LC modem: Using it with Apple Computers

=====

Article Created: 21 October 1985

Article Change History

02/09/93 - UPDATED

- Racal-Vadic changed name to Racal Datacom.

Modem type:

AT&T 103/212A series; 1200 or 300 bps

Instruction set used:

None.

Hardware configuration:

Five front panel status indicators. Modem is answer-only, with external dial telephone needed to originate call. Control buttons on front select either voice or data mode/voice mode disables answer operation.

Software configuration:

No software controls for modem.

Interface type:

RS-232 DB-25S (DCE) connector, full or half duplex operation.

Modem interface packages, by computer:

Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

Macintosh:

MacTerm or other terminal software,;Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

NOTE: This modem cannot originate calls - external telephone is needed if user wishes to dial out.

Racal-Vadic is now Racal Datacom.

Copyright 1985, 1993, Apple Computer, Inc.

Tech Info Library Article Number:1312