



Tech Info Library

Anchor Volksmodem 12 modem: Using it with all Apples

Revised: 10/21/85
Security: Everyone

Anchor Volksmodem 12 modem: Using it with all Apples

=====

Modem type:

AT&T 103/212A series; 1200, 0-300 bps.

Instruction set used:

Limited HAYES Compatible with only the S0 through S5 register functions supported.

Hardware configuration:

Two LEDs on the modem's front indicate HS (high-speed, 1200 bits/sec) and CD (carrier detect) functions. Modem runs off of +12V plug in power supply. Built-in speaker is used to monitor operation and diagnostics.

Software configuration:

Microprocessor-controlled intelligent modem with auto-dial and auto-answer functions.

Interface type:

RS-232 signal interface with unique five pin DIN connector; full duplex operation. Special Anchor Volkscable cables allow connection to all Apple computers.

Modem interface packages, by computer:

Apple IIe (Super Serial card):

Access II or other terminal software; Anchor cable type A-12 for hardware connection.

Apple IIc:

Access II or other terminal software; Anchor cable type H for hardware connection.

Apple III:

Access III or other terminal software; Anchor cable type A-12 for hardware connection.

Macintosh:

..TIL01320-Anchor_Volksmodem_12_modem-Using_it_with_all_Apples.pdf

MacTerm or other terminal software; Anchor cable type G for hardware connection.

Macintosh XL:

MacTerm or other terminal software; Anchor cable type A-12 for hardware connection.

Apple Technical Communications

Tech Info Library Article Number:1320