



# Tech Info Library

## Cermetek 1200 Modem: Using it with all Apples

Revised: 10/21/85  
Security: Everyone

Cermetek 1200 Modem: Using it with all Apples

=====

### Modem type:

AT&T 103 / 212A series; 1200, 0-300 bps.

### Instruction set used:

Fully HAYES compatible.

### Hardware configuration:

Seven LED indicators on front panel give modem and data status. Front panel switches allow voice or data operation. Call progress circuits detect dial, busy, ring-back, modem answer, or human voice. Modem runs off 117VAC, 60Hz.

### Software configuration:

Microprocessor controlled intelligent modem with auto-dial and auto-answer functions.

### Interface type:

RS-232 DB-25S (DCE) connector, full duplex operation.

### Modem interface packages, by computer:

#### Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

#### Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

#### Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

#### Macintosh:

# ..TIL01324-Cermetek\_1200\_Modem-Using\_it\_with\_all\_Apples\_(TA30147).pdf

MacTerm or other terminal software; Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

Apple Technical Communications

Tech Info Library Article Number:1324