



Tech Info Library

Apple Modem 300/1200: Configuring it with the Apple IIe

Revised: 3/3/86
Security: Everyone

Apple Modem 300/1200: Configuring it with the Apple IIe

=====

I. Switch settings

A. For 300 baud:

1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7
	ON	X			X	X	X	X		ON	X		X	X		X	
SW1										SW2							
	OFF		X	X							OFF		X		X		X
		1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

2. Modem:

UP				X
DOWN	X			
	1	2	3	
	CD	BC	DTR	

-- Switch 2 can be up or down; it isn't used.

B. For 1200 baud:

1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7
	ON		X	X	X	X	X	X		ON	X		X	X		X	
SW1										SW2							
	OFF	X									OFF		X		X		X
		1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

2. Modem:

UP		X	X
DOWN	X		
	1	2	3
	CD	BC	DTR

II. Connection:

A. Cable IIe: Apple Service Part Number 590-0121

Super Serial Interface Card DB-25	Apple Modem 300/1200 DB-9
1	8
2	9
3	5
6	2
7	3
8,5	7
20	6

Apple Technical Communications

Tech Info Library Article Number:1773