



Tech Info Library

AppleShare PC: How To Change the Printer Timeout Parameter

Revised: 9/18/89
Security: Everyone

AppleShare PC: How To Change the Printer Timeout Parameter

=====

This article last reviewed: 31 August 1989

TOPIC -----

I am trying to permanently change the printer timeout parameter in AppleShare PC 1.x. I can change the parameter, but whenever the machine is restarted, the parameter is reset to default.

DISCUSSION -----

The printer timeout parameter should stay as set even if the machine is restarted. We tested this on an IBM-XT running AppleShare PC 1.2.

Make sure that you reply "Yes" to the question:

Connect automatically at startup?

in the LaserWriter Connect window.

Another way to ensure that the timeout parameter stays after restart is to use the ANET command CONNECT in the PC AUTOEXEC.BAT file. Example:

```
ANET CONNECT LPT1: N(Printer Name) P(LaserWriter) D(timeout)
```

Please refer to the AppleTalk PC Update of the AppleTalk PC Printer Driver, part no 031-1031-A, for more information.

Copyright 1989 Apple Computer, Inc.

Tech Info Library Article Number:4339