



Tech Info Library

System 7: Workaround for 32-bit Incompatible Boards

Revised: 6/10/91
Security: Everyone

System 7: Workaround for 32-bit Incompatible Boards

=====

Article Created: 5 June 1991

Article Change History

08/21/92 - REVIEWED

- For technical accuracy; edited.

TOPIC -----

If a computer is set to 32-bit mode under System 7 and has a 32-bit incompatible board installed, you get an error chime at startup and a sad Macintosh on the screen, or both. How do you fix the problem?

DISCUSSION -----

To fix this, do the following:

- Remove the incompatible board or boards.
 - If you still have your video card installed (assuming it's not the incompatible card), start up from a 6.0.x floppy and you will get a dialog prompting you to change to 24-bit addressing.
- OR -
- If you don't have your video card, start up from your System 7 and reset the Parameter RAM by holding down Command-Option-p-r at start up.

These procedures will reset the addressing to 24-bit mode.

Copyright 1991, 1992, Apple Computer, Inc.

Tech Info Library Article Number:7275