



Tech Info Library

System Errors 7.0.1: Negative Codes (-299 to -5553) (11/95)

Revised: 4/21/97
Security: Everyone

System Errors 7.0.1: Negative Codes (-299 to -5553) (11/95)

Article Created: 31 January 1992
Article Reviewed/Updated: 29 November 1995

TOPIC -----

The following list provides an explanation of system errors -299 to -5553 as it relates to system software version 7.0.1.

Here's an explanation of two symbols used in the lists:

[Items listed in brackets are old result code meanings]
???? This information wasn't available.

DISCUSSION -----

Notification Manager Error

-299 nmTypeError Invalid qType--must be ORD(nmType)

Start Manager Errors

-290 smSDMInitErr SDM could not be initialized.
-291 smSRTInitErr Slot Resource Table could not be initialized.
-292 smPRAMInitErr Slot Resource Table could not be initialized.
-293 smPriInitErr Cards could not be initialized.
-300 smEmptySlot No card in slot
-301 smCRCFail CRC check failed for declaration data
-302 smFormatErr FHeader Format is not Apple's
-303 smRevisionErr Wrong revision level
-304 smNoDir Directory offset is Nil
-305 smLWTstBad Long Word test field <> \$5A932BC7.
-306 smNosInfoArray No sInfoArray. Memory Mgr error.
-307 smResrvErr Fatal reserved error. Reserved field <> 0.
-308 smUnExBusErr Unexpected Bus Error
-309 smBLFieldBad ByteLanes field was bad.
-310 smFHBblockRdErr Error occurred during _sGetFHeader.
-311 smFHBblkDispErr Error occurred during _sDisposePtr (Dispose of FHeader block).

-312	smDisposePErr	_DisposePointer error
-313	smNoBoardsRsrc	No Board sResource.
-314	smGetPErr	Error occured during _sGetPRAMRec (See SIMStatus).
-315	smNoBoardId	No Board Id.
-316	smIntStatVErr	The InitStatusV field was negative after primary or secondary init.
-317	smIntTblVErr	An error occured while trying to initialize the Slot Resource Table.
-318	smNoJumpTbl	SDM jump table could not be created.
-319	smBadBoardId	BoardId was wrong, re-init the PRAM record.
-320	smBusErrTO	BusError time out.
-330	smBadRefId	Reference Id not found in list
-331	smBadsList	Bad sResource [sList] structure: Id1<Id2<Id3 ... format is not followed.
-332	smReservedErr	Reserved field not zero
-333	smCodeRevErr	Code revision is wrong
-334	smCPUErr	Code revision is wrong
-335	smsPointerNil	LPointer is nil {From sOffsetData. If this error occurs, check sInfo rec for more information.}
-336	smNilsBlockErr	Nil sBlock error {Don't allocate and try to use a nil sBlock}
-337	smSlotOOBErr	Slot out of bounds error
-338	smSelOOBErr	Selector out of bounds error; function not implemented
-339	smNewPErr	_NewPtr error
-340	smBlkMoveErr	_BlockMove error
-341	smCkStatusErr	Status of slot = fail.
-342	smGetDrvrNamErr	Error occured during _sGetDrvrName.
-343	smDisDrvrNamErr	Error occured during _sDisDrvrName.
-344	smNoMoresRsrcs	No more sResources *OR*
-344	smNoMoresResources	Specified sResource data structure not found
-345	smsGetDrvrErr	Error occurred during _sGetDriver.
-346	smBadsPtrErr	Bad pointer was passed to sCaldSPointer function
-347	smByteLanesErr	ByteLanes field in card's format block was determined to be zero
-348	smOffsetErr	Offset was too big (temporary, should be fixed)
-349	smNoGoodOpens	No opens were successfull in the loop.
-350	smSRTOvrFlErr	SRT over flow.
-351	smRecNotFnd	Record not found in the SRT.

Device Manager Slot Support Errors

-360	slotNumErr	invalid slot # error
-400	gcrOnMFMErr	gcr format on high density media error

Edition Manager Errors

-450	editionMgrInitErr	Manager not initialized or could not load package
-451	badSectionErr	Not a valid section type
-452	notRegisteredSectionErr	Not registered
-454	badSubPartErr	Bad edition container spec or invalid edition container
-460	multiplePublisherWrn	Already is a publisher
-461	containerNotFoundWrn	Alias was not resolved
-463	notThePublisherWrn	Not the publisher

SCSI Manager Errors

-470 scsiBadPBErr invalid field(s) in the parameter block
-471 scsiOverrunErr attempted to transfer too many bytes
-472 scsiTransferErr write flag conflicts with data transfer phase
-473 scsiBusTOErr bus error during transfer
-474 scsiSelectTOErr scsiSelTO exceeded (selection failed)
-475 scsiTimeOutErr scsiReqTO exceeded
-476 scsiBusResetErr the bus was reset, so your request was aborted
-477 scsiBadStatus non-zero (not "Good") status returned
-478 scsiNoStatusErr device did not go through a status phase
-479 scsiLinkFailErr linked command never executed
-489 scsiUnimpVctErr unimplemented routine was called

SysErrs used instead of inline \$A9FF & \$ABFF

-490 userBreak user debugger break
-491 strUserBreak user debugger break - display string on stack
-492 exUserBreak user debugger break - execute commands on stack

QuickDraw Error

-500 rgnTooBigErr Bitmap would convert into a region greater than 64 KB

Text Edit Error

-501 teScrapSizeErr scrap item too big for text edit record

O/S Error

-502 hwParamrErr bad selector for _HWPriv

Processes Errors

-600 procNotFound No eligible process with specified process
 serial number
-601 memFragErr Not enough room to launch application
 with special requirements
-602 appModeErr Memory mode is 32-bit, but application is
 not 32-bit clean
-603 protocolErr app made module calls in improper order
-604 hardwareConfigErr hardware configuration not correct for call
-605 appMemFullErr Partition size specified in 'SIZE' resource is
 not big enough for launch
-606 appIsDaemon Application is background-only
-607 bufferIsSmall Buffer is too small
-608 noOutstandingHLE No outstanding high-level event
-609 connectionInvalid Connection is invalid
-610 noUserInteractionAllowed Attempted PostHighLevelEvent from
 background and no session yet established

Memory Dispatch Errors

-620 notEnoughMemoryErr Insufficient physical memory
-621 notHeldErr Specified range of memory is not held
-622 cannotMakeContiguousErr Cannot make specified range contiguous
-623 notLockedErr Specified range of memory is not locked
-624 interruptsMaskedErr Called with interrupts masked

-625 cannotDeferErr Unable to defer additional user functions

DatabaseAccess (Pack 13) Errors

-800 rcDBNull The data item was NULL
-801 rcDBValue Data available or successfully retrieved
-802 rcDBError Error executing function
-803 rcDBBadType Next data item not of requested data type
-804 rcDBBreak Function timed out
-805 rcDBExec Query currently executing
-806 reDBBadSessID Session ID is invalid
-807 rcDBBadSessNum Invalid session number
-808 rcDBBadDDEV Couldn't find the specified database extension,
or error occurred in opening database extension
-809 rcDBAsyncNotSupp The database extension does not support
asynchronous calls
-810 rcDBBadAsyncPB Invalid parameter block specified
-811 rcDBNoHandler There is no handler for this data type
installed for the current application
-812 rcDBWrongVersion Wrong version number
-813 rcDBPackNotInitd The InitDBPack function has not yet been called

Help Manager Errors

-850 hmHelpDisabled Help balloons are not enabled
-851 hmResNotFound ????
-852 hmMemFullErr ????
-853 hmBalloonAborted Because of constant cursor movement,
the help balloon wasn't displayed
-854 hmSameAsLastBalloon Menu and item are same as previous menu and item
-855 hmHelpManagerNotInitd Help menu not set up
-856 hmBadSelector ????
-857 hmSkippedBalloon No balloon content to fill in
-858 hmWrongVersion Wrong version of Help Manager resource
-859 hmUnknownHelpType Help message record contained a bad type
-860 hmCouldNotLoadPackage ????
-861 hmOperationUnsupported Bad method parameter
-862 hmNoBalloonUp No balloon showing
-863 hmCloseViewActive User using CloseView won't let you remove balloon

AppleTalk - PPC Toolbox Errors

-900 notInitErr PPC Toolbox has not been initialized yet
-902 nameTypeErr Invalid or inappropriate locationKindSelector
in location name
-903 noPortErr Invalid port name; Unable to open port or bad
port reference number
-904 noGlobalsErr System unable to allocate memory, critical error
-905 localOnlyErr Network activity is currently disabled
-906 destPortErr Port does not exist at destination
-907 sessTableErr PPC Toolbox is unable to create a session
-908 noSessionErr Invalid session reference number
-909 badReqErr Bad parameter or invalid state for this operation
-910 portNameExistsErr Another port is already open with this name
-911 noUserNameErr User name unknown on destination machine
-912 userRejectErr Destination rejected the session request

-915	noResponseErr	Unable to contact application
-916	portClosedErr	The port was closed
-917	sessClosedErr	The session has closed
-919	badPortNameErr	PPC port record is invalid
-922	noDefaultUserErr	User has not specified owner name in Sharing Setup control panel
-923	notLoggedInErr	Default user reference number does not yet exist
-924	noUserRefErr	Unable to create a new user reference number
-925	networkErr	An error has occurred in the network
-926	noInformErr	PPCStart failed because target application did not have an inform pending
-927	authFailErr	User's password is wrong
-928	noUserRecErr	Invalid user reference number
-930	badServiceMethodErr	Service method is other than ppcServiceRealTime
-931	badLocNameErr	Location name is invalid
-932	guestNotAllowedErr	Destination port requires authentication

AppleTalk - NBP Errors

-1024	nbpBuffOvr	Buffer overflow in LookupName
-1025	nbpNoConfirm	Name not confirmed on ConfirmName
-1026	nbpConfDiff	Name confirmed at different socket
-1027	nbpDuplicate	Duplicate name exists already
-1028	nbpNotFound	Name not found on remove
-1029	nbpNISErr	Error trying to open the NIS

ASP Errors (XPP driver)

-1066	aspBadVersNum	Server cannot support this ASP version
-1067	aspBufTooSmall	Buffer too small
-1068	aspNoMoreSess	No more sessions on server
-1069	aspNoServers	No servers at that address
-1070	aspParamErr	Parameter error
-1071	aspServerBusy	Server cannot open another session
-1072	aspSessClosed	Session closed
-1073	aspSizeErr	Command block too big
-1074	aspTooMany	Too many clients (server error)
-1075	aspNoAck	No ack on attention request (server err)

AppleTalk - ATP Errors

-1096	reqFailed	Request to contact router failed: retry count exceeded
-1097	tooManyReqs	Too many concurrent requests
-1098	tooManySkts	Too many concurrent responding-sockets
-1099	badATPSkt	Bad ATP-responding socket
-1100	badBuffNum	Bad response buffer number specififed
-1101	noRelErr	No release received
-1102	cbNotFound	Control Block not found; no pending asynchronous calls
-1103	noSendResp	AddResponse issued without SendResponse
-1104	noDataArea	No data area for request to MPP
-1105	reqAborted	ERdCancel function called for this ERead [SendRequest aborted by RelTCB]

Data Stream Protocol - DSP driver Errors

-1273	errOpenDenied	Open request denied by recipient
-------	---------------	----------------------------------

-1274	errDSPQueueSize	Send or receive queue is too small
-1275	errFwdReset	Read terminated by forward reset
-1276	errAttention	Attention message too long
-1277	errOpening	Attempt to open connection failed
-1278	errState	Bad connection state for this operation
-1279	errAborted	Request aborted by dspRemove or dspClose function
-1280	errRefNum	Bad connection reference number

HFS Errors

-1300	fidNotFound	File ID not found [No file thread exists]
-1301	fidExists	File id already exists
-1302	notAFileErr	Specified file is a directory
-1303	diffVolErr	Files on different volumes
-1304	catChangedErr	Catalog has changed and CatPosition may be invalid
-1305	desktopDamagedErr	The desktop database has become corrupted – the Finder will fix this, but if your application is not running with the Finder, use DTRreset or DTDelete

AppleEvent Errors

-1700	errAECOercionFail	Data could not be coerced to the requested descriptor type
-1701	errAEDescNotFound	Descriptor record was not found
-1702	errAECorruptData	Data in an Apple event could not be read
-1703	errAEWrongDataType	Wrong descriptor type
-1704	errAENotAEDesc	Not a valid descriptor record
-1705	errAEBadListItem	Operation involving a list item failed
-1706	errAENewerVersion	Need a newer version of the Apple Event Manager
-1707	errAENotAppleEvent	Event is not an Apple event
-1708	errAEEEventNotHandled	Event wasn't handled by an Apple event handler
-1709	errAERReplyNotValid	AERresetTimer was passed an invalid reply
-1710	errAEUnknownSendMode	Invalid sending mode was passed
-1711	errAEWaitCanceled	User canceled out of wait loop for reply or receipt
-1712	errAETimeout	Apple event timed out
-1713	errAENoUserInteraction	No user interaction allowed
-1714	errAENotASpecialFunction	Wrong keyword for a special function
-1715	errAEPParamMissed	Handler did not get all required parameters
-1716	errAEUnknownAddressType	Unknown Apple event address type
-1717	errAEHandlerNotFound	No handler found for an Apple event or a coercion
-1718	errAERReplyNotArrived	Reply has not yet arrived
-1719	errAEIllegalIndex	Not a valid list index

AppleTalk - ATP Errors

-3101	buf2SmallErr	Packet too large for buffer; partial data returned
-3102	noMPPErr	No MPP error
-3103	ckSumErr	Check sum error
-3104	extractErr	Extraction error
-3105	readQErr	Read queue error
-3106	atpLenErr	ATP length error
-3107	atpBadRsp	ATP bad response error
-3108	recNotFnd	Record not found

-3109 sktClosedErr Socket closed error

Print Manager w/LaserWriter

-4096 ??? No free Connect Control Blocks available
-4097 ??? Bad connection reference number
-4098 ??? Request already active
-4099 ??? Write request too big
-4100 ??? Connection just closed
-4101 ??? Printer not found, or closed

File Manager Extensions Errors

-5000 accessDenied Incorrect access for this file/folder
-5006 DenyConflict Permission/Deny mode conflicts with the current
 mode in which this fork is already open
-5015 NoMoreLocks Byte range locking failure from Server
-5020 RangeNotLocked Attempt to unlock an already unlocked range
-5021 RangeOverlap Attempt to lock some of an already locked range

AFP Errors (XPP driver)

-5000 afpAccessDenied AFP Access denied
-5001 afpAuthContinue AFP Authorization continue
-5002 afpBadUAM AFP Bad UAM
-5003 afpBadVersNum AFP Bad version number
-5004 afpBitmapErr AFP Bit map error
-5005 afpCantMove AFP Can't move error
-5006 afpDenyConflict AFP Deny conflict
-5007 afpDirNotEmpty AFP Dir not empty
-5008 afpDiskFull AFP Disk full
-5009 afpEofError AFP End-of-File error
-5010 afpFileBusy AFP File busy
-5011 afpFlatVo AFP Flat volume
-5012 afpItemNotFound AFP Information not found
-5013 afpLockErr AFP Lock error
-5014 afpMiscErr AFP Misc error
-5015 afpNoMoreLocks AFP No more locks
-5016 afpNoServer AFP No server
-5017 afpObjectExists AFP Object already exists
-5018 afpObjectNotFound AFP Object not found
-5019 afpParmErr AFP Parm error
-5020 afpRangeNotLocked AFP Range not locked
-5021 afpRangeOverlap AFP Range overlap
-5022 afpSessClosed AFP Session closed
-5023 afpUserNotAuth AFP User not authorized
-5024 afpCallNotSupported AFP Call not supported
-5025 afpObjectTypeErr AFP Object type error
-5026 afpTooManyFilesOpen AFP Too many files open
-5027 afpServerGoingDown AFP Server going down
-5028 afpCantRename AFP Can't rename
-5029 afpDirNotFound AFP Directory not found
-5030 afpIconTypeError Size of new icon and one it replaces don't match
-5031 afpVolLocked Volume is Read-Only
-5032 afpObjectLocked Object is M/R/D/W inhibited

SysEnviron Errors

-5500 envNotPresent SysEnviron trap not present - returned by glue.
-5501 envBadVers Version non-positive
-5502 envVersTooBig Version bigger than call can handle

Gestalt Errors

-5550 gestaltUnknownErr Could not obtain the response
-5551 gestaltUndefSelectorErr Undefined selector
-5552 gestaltDupSelectorErr Selector already exists
-5553 gestaltLocationErr Function not in system heap

Article Change History:

29 Nov 1995 - Corrected minor typo.
07 Dec 1994 - Corrected spelling.
25 Sep 1992 - Reviewed for technical accuracy.

Support Information Services

Copyright 1992-95, Apple Computer, Inc.

Tech Info Library Article Number:9804