



# Tech Info Library

## LaserWriter Select 310: Memory Requirements (3/95)

Revised: 3/20/95  
Security: Everyone

LaserWriter Select 310: Memory Requirements (3/95)

Article Created: 9 February 1993  
Article Reviewed/Updated: 20 March 1995

TOPIC -----

This article discusses the memory requirements and configurations of the LaserWriter Select 310.

DISCUSSION -----

### Letter-Size Pages

The LaserWriter Select 310 ships with 1MB of ROM and 1.5MB RAM on the logic board. With this amount of memory, you can print letter-size pages and download up to three PostScript typefaces to the printer.

### Legal-Size Pages

If you want to print legal-size documents, download additional Postscript fonts, or print documents with complex graphics then you must install either the 1MB or 4MB memory upgrade. If you print a legal-size page from the multi-purpose tray without upgrading the memory, your page prints on the legal paper, however on in a letter-size page area (8.5x11).

### Possible Memory Configurations

Built-in	Expansion	Total Memory
1.5MB	0	1.5MB
1.5MB	1MB	2.5MB (required for legal-size paper)
1.5MB	4MB	5.5MB (maximum amount)

The LaserWriter Select 310 has one memory expansion DRAM SIMM slot that uses industry-standard fast page mode 100ns 72-pin memory SIMMs. Only 1MB and 4MB SIMMs are supported in the LaserWriter Select 310.

The LaserWriter Select 310 memory is NOT interchangeable with the LaserWriter Select 300, because their SIMMs are different sizes.

Article Change History:

20 Mar 1995 - Clarified legal-size paper information.

30 Nov 1993 - Clarified information on memory

Support Information Services

Copyright 1993-95, Apple Computer, Inc.

Tech Info Library Article Number:11519