



Tech Info Library

Apple IIe: Brother EM-701 Typewriter Interface

Revised: 5/25/89
Security: Everyone

Apple IIe: Brother EM-701 Typewriter Interface

=====

This article last reviewed: 28 September 1987

Here's how to interface a Brother EM-701 typewriter to an Apple IIe with a Super Serial Card. This information was supplied by Merlin's Computers, Covina, California.

Brother EM-701 Switch Settings

SW-1-1 ON
1-2 OFF
1-3 ON
1-4 OFF
1-5 OFF
1-6 OFF
1-7 OFF
1-8 ON

SW-2-1 OFF
2-2 OFF These set the typewriter to 9600 baud.
2-3 OFF
2-4 OFF

SW-2 Controls the baud rate of the typewriter. If the typewriter is set to 8-bit transmission, the typewriter will need a different print wheel because of the \$ and %. The characters don't appear in the 8-bit form or have problems printing.

Super Serial Card

(The Super Serial Card needs to have the jumper block pointing toward 'Terminal').

SW-1-1 OFF
1-2 OFF

1-3 OFF
1-4 ON
1-5 ON
1-6 ON
1-7 ON

SW-2-1 ON
2-2 OFF
2-3 OFF
2-4 OFF
2-5 ON
2-6 ON
2-7 OFF

Apple Computer, Inc., is not responsible for the content of this article.

Merlin's Computers

Copyright 1989 Apple Computer, Inc.

Tech Info Library Article Number:792