



Tech Info Library

ImageWriter Printer Configuration Table

Revised: 1/30/92
Security: Everyone

ImageWriter Printer Configuration Table

=====

This article last reviewed: 02 November 1988

System	SW-1	SW-2	CABLE REQUIRED
	12345678	1234	Part Number
Apple III	11001100	1100	590-0029 and 590-0037B
Macintosh	11001100	1100	590-0169
Lisa/Macintosh XL	11001100	1100	590-0029 and 590-0037B
Apple IIc	11001100	1100	590-0191A
Super Serial	11001100	1100	590-0037B
High Speed Serial	11001100	0011	590-0037B

NOTE: 0 = OFF = OPEN
1 = ON = CLOSED

Apple III Driver Configuration

Driver	Data Configuration Block											
	0	1	2	3	4	5	6	7	8	9	A	B
RS232	0E	00	00	00	00	00	13	11	DF	84	50	80
PRINTER	0E	00	00	00	00							

Super Serial Card Configuration

	1	2	3	4	5	6	7
SW1	Off	Off	Off	On	Off	On	On
SW2	On	Off	Off	Off	On	Off	Off

NOTE: Jumper block should be pointing towards terminal.

High Speed Serial Card Configuration

_____	_1_ _2_ _3_ _4_ _5_ _6_ _7_
Switches	On Off On On Off Off Off

NOTE: The High Speed card must have the PROM P8 installed.

Copyright 1988 Apple Computer, Inc.

Tech Info Library Article Number:1427