



Tech Info Library

Apple IIC: Cable structure to Nec 2015 Spinwriter

Revised: 11/7/85
Security: Everyone

Apple IIC: Cable structure to Nec 2015 Spinwriter

```
=====
APPLE IIC                                NEC 2015 SPINWRITER

2-----3
3-----7
4-----2
5-----19
                                4,5,6,8: Jumpered
```

NEC Dip switch settings:

Switch series 1: all off except #8
Switch series 2: all off
Switch series 3: all off except #4,6,7,8.

Clinton Computer, MD

Tech Info Library Article Number:1447