



# Tech Info Library

## Macintosh SE/30: Recommended Way To Connect Kodak DataShow

Revised: 9/28/92  
Security: Everyone

Macintosh SE/30: Recommended Way To Connect Kodak DataShow

=====

Article Created: 15 June 1989

### Article Change History

-----

09/28/92 - REVIEWED

- For technical accuracy.

### TOPIC -----

Connecting the Kodak DataShow to the Macintosh SE/30 created quite a controversy as to which chip and pin on the logic board contains the signal for the pixel clock.

### DISCUSSION -----

Initially, an article stated that pin 1 of UG6 was the correct location to find the pixel clock (according to the engineer who designed the logic board). Soon thereafter, Kodak recommended pin 1 of UG7.

A copy of the Macintosh SE/30 logic board schematics showed that both pin 1 of UG6 and pin 1 of UG7 are tied together and generate the same signal. In fact, several chips on the logic board, beside UG6 and UG7, generate the pixel clock signal. Engineers confirmed this with a continuity meter and verified a connection between pin 1 of UG6 and pin 1 of UG7. An oscilloscope also verified that the signals were identical.

Tech Comm engineers obtained a Kodak DataShow unit and successfully installed it on pin 1 of UG6 and pin 1 of UG7. Perhaps other factors caused the unsuccessful installations of the DataShow unit on UG6 and UG7. For example, perhaps pin 1 and pin 2 were shorted together. It is also possible that a good connection was not made between pin 1 and the DataShow interface.

Recommendation: Use pin 1 of UG7. This is for two reasons:

- 1) Pin 1 of UG7 is what Kodak recommends.
- 2) It is easier to install the DataShow connector on pin 1 of UG7.

Copyright 1989 Apple Computer, Inc.

Tech Info Library Article Number:4089