



Tech Info Library

Apple 5.25 Drive: Controller Card Pinouts

Revised: 8/20/91
Security: Everyone

Apple 5.25 Drive: Controller Card Pinouts

=====

Article Created: 6 August 1991
Article Last Reviewed:
Article Last Updated:

TOPIC -----

What are the pinouts for the Apple 5.25 Drive controller card?

DISCUSSION -----

The pinouts for the Apple 5.25 Drive controller card are:

Pin #	Description
-----	-----
1,2,3	Gnd
4	n/a
5	-12 volts
6	+5 volts
7,8	+12 volts
9	Drive 2 Select
10	Write Protect Input
11	Stepper Motor Phase 0
12	Stepper Motor Phase 1
13	Stepper Motor Phase 2
14	Stepper Motor Phase 3
15	Write Request
16	n/a
17	Drive 1 Select
18	Read Data
19	Write Data

Copyright 1991 Apple Computer, Inc.

Tech Info Library Article Number:8015