



Tech Info Library

LaserWriter: RS-232 Direct Cable Pinouts To The Macintosh Plus

Revised: 7/16/92
Security: Everyone

LaserWriter: RS-232 Direct Cable Pinouts To The Macintosh Plus

Article Created: 19 October 1988
Article Last Reviewed: 1 July 1992
Article Last Updated:

Macintosh			Laserwriter		Signal	
Signal Mini-Circular 8			(DB-25)	Signal		
Name	pin		pin	Name	Comments	
No connection			1	GND	Chassis Ground	
GND	4	<->	7	GND	Signal Ground	
RxD+	8	<->	7	GND	Signal Ground	
TxD-	3	<->	3	Rx	Macintosh data output: Transmit data, negative going Laserwriter data input: Receive data	
Hsk Out	1	<->	5,6,8		Power detection; ready signal	
RxD-	5	<->	2	Tx	Laserwriter signal output: Transmit data Macintosh signal input: Receive data, negative going	

Copyright 1988 Apple Computer, Inc.

Tech Info Library Article Number:209