



Tech Info Library

Macintosh Portable Data Modem 2400: Pinouts

Revised: 9/18/89
Security: Everyone

Macintosh Portable Data Modem 2400: Pinouts

=====

This article last reviewed: 18 September 1989

Macintosh Portable Data Interface

Pin	Pin Name	Definition
---	-----	-----
1	/Modem_Power	System power status
2	Ground	Ground
3	/RTS	Request to send
4	/DCD	Data Carrier Detect
5	RxD	Receive data
6	/CTS	Clear to send
7	Modem_sound	Analog sound output
8	TxD	Transmit data
9	/RI_EXT	Ring indicator
10	-5 VDC	Power (switchable)
11	+5 VDC	Power (unswitched)
12	/DTR	Data terminal ready
13	V1	Sound volume control bit (Least significant)
14	V3	Sound volume control bit (Most significant)
15	V2	Sound volume control bit (Middle significant)
16	/Modem_Ins	Modem installed
17	/Modem_Busy	Modem busy
18	MS_Enable	Modem sound enable

Copyright 1989 Apple Computer, Inc.

Tech Info Library Article Number:4480